

# 365 True-rms AC/DC Clamp Meter

Rugged meters where access is difficult

The Fluke 365 is a new, innovative Fluke clamp meter, offering a thin, small jaw design that makes it easy to get around tightly packed wires. The detachable jaw on a flexible lead makes access to wires and viewing the display easier than ever. The Fluke 365 measures current up to 200 A ac and dc with true-rms measurement.

**New**



**True  
RMS**



## Technical Data

### Measurement capability

- 200 A ac and dc current measurement with detachable jaw
- 600 V ac and dc voltage measurement
- True-rms ac voltage and current for accurate measurements on non-linear signals
- 6000  $\Omega$  resistance measurement with continuity detection

### Features

- Detachable jaw makes accessing wires and viewing the display easier
- Built in flashlight/torch allows for easy illumination and identification of wires
- CAT III 600 V safety rating
- Compact design fits in your hand and can be used while wearing personal protective equipment
- State of the art signal processing allows for use in noisy electrical environments while providing stable readings
- Large, easy to read backlight display automatically sets the correct measurement range so you do not need to change switch positions while taking a measurement
- Three-year warranty
- Soft case

## Specifications

| Fluke 365        | Range         | Resolution | Accuracy       |
|------------------|---------------|------------|----------------|
| AC current       | 200 A         | 0.1 A      | 2 % ± 5 digits |
| DC current       | 200 A         | 0.1 A      | 2 % ± 5 digits |
| AC voltage       | 600 V         | 0.1 V      | 2 % ± 5 digits |
| DC voltage       | 600 V         | 0.1 V      | 2 % ± 5 digits |
| Resistance       | 6000 Ω        | 0.1 Ω      | 1 % ± 5 digits |
| True-rms         | •             |            |                |
| Continuity       | •             |            |                |
| Hold             | •             |            |                |
| Backlight        | •             |            |                |
| Flashlight/torch | •             |            |                |
| Wire capacity    | 17 mm         |            |                |
| Safety rating    | CAT III 600 V |            |                |

## Ordering information

**365 True-rms AC/DC  
Clamp Meter**

## Included

Clamp meter, test leads, soft case, users manual.

**Fluke.** *Keeping your world up and running.®*

**Fluke Corporation**  
PO Box 9090, Everett, WA 98206 U.S.A.

**Fluke Europe B.V.**  
PO Box 1186, 5602 BD  
Eindhoven, The Netherlands

**For more information call:**  
In the U.S.A. (800) 443-5853 or  
Fax (425) 446-5116  
In Europe/M-East/Africa +31 (0) 40 2675 200 or  
Fax +31 (0) 40 2675 222  
In Canada (800)-36-FLUKE or  
Fax (905) 890-6866  
From other countries +1 (425) 446-5500 or  
Fax +1 (425) 446-5116  
Web access: <http://www.fluke.com>

©2010-2011 Fluke Corporation.  
Specifications subject to change without notice.  
Printed in U.S.A. 3/2011 3805299B D-EN-N

**Modification of this document is not permitted  
without written permission from Fluke Corporation.**